## **Rack Mount Power Distribution Unit**





Rack Mount Power Distribution Unit: 3 Phase 400VAC, IEC30309 32A 3P+N+E plug input, 18 ways C13 + 6 ways C19 output. With 3× 32A Air Circuit Breaker & Digital Amps / Volts Meter.

| PRODUCT LABEL         |  |
|-----------------------|--|
| Product Name          | Designated Power Distribution Unit for Cabinet |
| Item Code             | 01230401 (Model: AUE2211H1-24AVKTVB-1806)      |
| Rating Voltage        | 400 VAC 50/60 Hz                               |
| Rating Current        | 3× 32A   |
| Max. Power            | 3× 8000 W                                      |
| Safety Authentication | CE, RoHS                                       |

## **Technical Specifications**

| ITEM                      | DESCRIPTION  |
|---------------------------|--|
| Socket Type               | [6× IEC320 C19 Socket] + [18× IEC320 C13 Socket]   |
| Socket Quantity           | 24 way   |
| Power Input               | Left end single input (Bottom feed power input)  |
| Bracket Install           | Inverse installation (OU)  |
| Cable with Plug           | IEC60309 plug (32A 3P + N + E)   |
| Control Function          | 3× 32A Air Circuit Breaker   |
| Protection Function       | 3-phase digital Amps / Volt Meter [1]  |
| Case                      | Black  |
| Cable Specifications      | 5 × 6.0 mm <sup>2</sup> × 3M   |
| Product Size (L×W×H mm)   | 1638 × 56 × 44.4   |
| Mounting Length           | 1617 mm  |
| Case Length               | 1585 mm  |
| Fittings                  | 2 pcs Ø6 $\times$ 16mm cross bolt, 2 pcs M6 float nut, 2 pcs removable brackets, 8pcs M3-6 fast pan screws |
| Interior Connection wire  | 2.5 mm² (14AWG)  |
| Interior Connection style | Group connection   |
| Fix the cable             | Cable clamp (21)   |

## Product Imag





IEC60309 plug (32A 3P+N+E)

## VertivCo.com

© 2019 Vertiv Co. All rights reserved. Vertiv, the Vertiv logo are trademarks or registered trademarks of Vertiv Co. All other names and logos referred to are trade names, trademarks or registered trademarks of their respective owners. While every precaution has been taken to ensure accuracy and completeness herein, Vertiv Co. assumes no responsibility, and disclaims all liability, for damages resulting from use of this information or for any errors or omissions. Specifications are subject to change without notice.